

Plant Hazard Analysis & Risk Assessment

Monitor
ABN: 76 159 267 679
143 Gunnedah Rd
Tamworth NSW 2340
Ph: 02 6755 6000
E: service@monitor.net.au

Model: BG Lift M250 Date: 11/09/2024



Person conducting assessment:

This Hazard Identification and Risk Assessment document is Model specific. It is based on the knowledge that all new machines of this model were/are produced to the same specification and design. It assumes all examples of this exact model currently in service to be as per the original specification, and to have been and continue to be operated and maintained in accordance with the Manufacturers requirements, and with all applicable statutory and regulatory requirements of an original example of the Model for which it was prepared. This Assessment must be reviewed by all stakeholders as required:

- Having regard to the manufacturers approved options
- Having regard to the general arrangement of miscellaneous equipment or facilities that may be provided on the plant according to the end users requirements or specification
- According to the particular circumstances under which the plant is used and maintained
- As new Hazards are identified and/or as risks are reassessed
- As existing risk control measures are revised or new risk control measures are introduced and implemented
- As and when work procedures are altered or revised
- Having regard to any unauthorised alterations or modifications made to the design or operation of the equipment

Monitor has made every attempt to identify all reasonably foreseeable operating circumstances in preparing this Assessment, however no guarantee as to the completeness of this Assessment is provided or implied. It is the responsibility of Owners, Employers and Operators to identify all hazards associated with the use of this equipment specifically applicable to the task to be carried out and to where the equipment is to be used or located. They must assess the risk potential for each of the identified hazards and ensure that all reasonably practicable steps are taken to ensure those risks are effectively controlled.

- All operators must be trained and competent in the safe use of this particular piece of equipment, and hold appropriate qualifications as required by applicable regulatory requirements
- Operators of the equipment to which this Plant Risk Assessment refers must read and understand the Instructions for Use and Warnings contained within the Operators Manual prior to use
- All Daily Pre-Start Checks, Routine and Periodic Inspections, Maintenance and Repairs to this equipment must be carried out in accordance with the requirements of AS2550.10-2006

© Monitor 2023

Revision: 01

ID	Description of	Hazard Potential	Activity	Risk control measures already	Risk	Supplementary risk control	Risk
•	Origin	Consequence		implemented		measures	score
1	Operator Competency						
1.1	Untrained operator, not following proper operating procedures. Distracted operator. Following a poor system of work. Operator working alone.	Crushing Impact Trauma	Set up Operation Maintenance	Operation instructions explained in operator's manual	C4 Extreme	Train operators on safe use of the plant. Operator training should include at least the following: • pre-operation inspections • safe operation of plant • regular maintenance tasks • understanding of plant operation • capabilities and limitations • emergency procedures Do not operate the plant unless proper training has been received. Ensure operator's manual is kept with the plant for reference. Do not operate the plant when distracted, ill, excessively fatigued, or under the influence of drugs or alcohol. Implement appropriate system of work based on manufacturer's recommendations (e.g. operating instructions shown in operator's manual).	B1 Low
1.2	Misuse Unauthorised use of plant	Crushing Impact Trauma	Operation	Operator's manual warns about not using the plant for other than its intended purpose.	C4 Extreme	Do not use the plant for any other purpose than its intended use as explained in the operator's manual. Do not operate the plant unless proper training has been received.	B1 Low

© Monitor 2023

Managing Director

Date: 11 Sep. 2024

Revision: 01

THIS DOCUMENT IS CONTROLLED – UNCONTROLLED WHEN PRINTED

Document Number: 01

Page:

ID	Description of	Hazard Potential	Activity	Risk control measures already	Risk	Supplementary risk control	Risk
	Origin	Consequence		implemented		measures	score
						Keys are not to remain in an unattended machine.	
2	Plant Limitations						
2.1	Plant overload causing - overturning - structural failure	Roll over Crushing	Driving Operation	Refer to the crane's maximum load table for the maximum outreach (minimum boom angle) so that the load can be lifted safely. Overload indicator and limiter provided which prevents overload from vertical loads/reach.	C4 Extreme	Learn and understand plant limitations. Do not exceed load capacity. Regularly inspect the plant as per maintenance schedule to ensure integrity of structural members.	A2 Low
2.2	Excessive incline causing plant to overturn	Roll over	Driving Operation	Maximum allowable slope outlined in operator's manual. Outriggers fitted to allow the chassis to be levelled. Auto levelling provided. Interlock provided to ensure that the outriggers are engaged and the chassis levelled before the crane can be slewed.	C3 High	Do not drive the plant over ground slopes which exceeds its limitations. Drive with tracks expanded to give better balance. Conduct site risk assessment to determine suitability of job site before starting any work.	B2 Low
2.3	Excessive wind force causing overturning.	Roll over	Operation	Maximum allowable wind speed outlined in operator's manual (12.5m/s).	C3 High	Do not operate the plant under excessive wind conditions. Know and understand plant limitations. Constantly monitor wind speed when operating in wind sensitive areas.	B2 Low
2.4	Drive acceleration	Crushing Being runover	Driving	Levers must be activated continuously in order to drive.	C3 High	Do not drive at fast speeds.	B2 Low

© Monitor 2023

Managing Director

THIS DOCUMENT IS CONTROLLED – UNCONTROLLED WHEN PRINTED

Document Number: 01

Revision: 01

Date: 11 Sep. 2024 Page:

ID	Description of	Hazard Potential	Activity	Risk control measures already	Risk	Supplementary risk control	Risk
	Origin	Consequence	_	implemented		measures	score
						Be aware of other persons near and around the plant. Maintain visual contact with the direction of travel.	
3	Plant at worksite						
3.1	Collision with - site infrastructure - other plant and/or pedestrians - overhead powerlines	Crushing Impact Electrocution	Set up Operation Driving Transport		C3 High	Beware of any obstructions around the work area; survey the area before moving the plant including powerlines. Beware of other plant and persons around the work area, in particular when travelling around corners or blind spots. Use spotter where required.	B2 Low
3.2	Load or parts of the crane entangled with fixed objects	Overturning Impact	Set up Operation		C5 Extreme	Plan lift beforehand, determine plant and load flight path before commencing a lift operation.	A2 Low
3.3	Plant positioned near or driven over large depressions / obstacles.	Roll over Collapse	Operation Driving	Operator's manual recommends avoiding working near ditches and trenches. ground.	C4 Extreme	Always maintain a safe distance from ditches, trenches or pit walls while operating plant. Plan a route to safely bring the plant to the job site. Avoid driving over large obstacles or depressions. Assess the ground conditions before setting up the plant.	B2 Low
4	Operation						
4.1	Damaged control panel	Crushing Impact	Set up Operation		C5 Extreme	Regularly inspect control panel.	B1 Low

Document Number: 01

Date: 11 Sep. 2024

Revision: 01

© Monitor 2023

THIS DOCUMENT IS CONTROLLED – UNCONTROLLED WHEN PRINTED

Page:

ID	Description of	Hazard Potential	Activity	Risk control measures already	Risk	Supplementary risk control	Risk
	Origin	Consequence		implemented		measures	score
4.2	Driving on steep ground	Overturning Crushing	Driving Set up	Slope limits during travel and whilst in use provided in operators manual.	A5 High	Carry out job site risk assessment to determine suitability of the site before commencing any work.	A1 Low
				Warning in manual that there is no automatic device for slope management.		Avoid driving on steep ground; find alternative routes whenever possible.	
				Interlock provided to ensure that the outriggers are engaged and the chassis levelled before		Do not stand on the lower side of the plant while driving on steep ground.	
				the crane can be slewed. Remote control permits operator to stand at a safe distance away from the plant.		Never drive across steep ground, always drive with the tracks parallel to ground inclination.	
4.3	Operator control	Roll over Impact	Operation	Model comes with remote control.	C5 Extreme	Operate the drive control levers gently in order to avoid abrupt and jerky movements.	B2 Low
						When driving, pay special attention to stability and the dimensions, especially the length, of the machine.	
4.4	Ballast fully extended during transit	Crushing Overturning	Operation	Operator's manual instructs the operator to ensure the ballast is not applied while travelling to prevent overloading the tracks.	B5 Extreme		A2 Low
4.5	Uncontrolled movement of plant components	Crushing Impact Shearing	Set up Operation Maintenance	Prestart inspection as per manufacturers recommendation.	C3 High	Follow manufacturer's instructions for attachment/removal of any items of plant.	B2 Low
			Cleaning Troubleshoot			Isolate power to plant and remove the main switch key when performing maintenance and cleaning tasks.	

© Monitor 2023

Document Number: 01

Date: 11 Sep. 2024

Revision: 01

THIS DOCUMENT IS CONTROLLED – UNCONTROLLED WHEN PRINTED

ID	Description of	Hazard Potential	Activity	Risk control measures already	Risk	Supplementary risk control	Risk
	Origin	Consequence		implemented		measures	score
						Install safety barriers around the working area to prevent unauthorised access.	
						Maintain a safe distance from moving parts of the plant.	
						Stay clear of components which may swing or drop unexpectedly.	
						Maintenance to be carried out by a competent person.	
4.6	Unintended operation of controls.	Crushing Impact	Set up Operation Maintenance Emergency	Control system has neutral position sensing. Controls automatically return to neutral when released.	D3 High	Do not operate the plant unless trained to do so.	A3 Medium
4.7	Maximum rated capacity is exceeded.	Crushing Impact	Set up Operation Maintenance	Overload indicator and limiter provided which prevents overload from vertical loads/reach.	C5 Extreme	Operators trained in the meaning of the load indicator.	B2 Low
4.8	Falling objects / suspended load	Impact Crushing	Operation	Crash hazard decal on plant	C3 High	Do not stand directly under material being lifted.	B2 Low
						Barricade work area under fall zone to create a no-go zone.	
4.9	Suspended load or parts of the crane entangled with fixed	Overturning	Set up Operation		C5 Extreme	Plan lift beforehand, determine crane and load flight path before commencing a lift operation.	A2 Low
	objects					Dogman to maintain constant communication (visual or audible) with crane operator.	
4.10	Lowering/raising and slewing of boom and, hook block.	Crushing Impact	Set up Operation Maintenance	Crush hazard decal present on boom.	C4 Extreme	Always maintain visual contact with moving parts of the plant a payload.	B2 Low
			Troubleshoot			Hard hat required especially with suspended loads.	

Title:
Authorised By:
© Monitor 2023

Plant Risk Assessment Managing Director **Document Number: 01**

Date: 11 Sep. 2024

Revision: 01

THIS DOCUMENT IS CONTROLLED – UNCONTROLLED WHEN PRINTED

ID	Description of	Hazard Potential	Activity	Risk control measures already implemented	Risk	Supplementary risk control	Risk
	Origin	Consequence		implemented		measures	score
						Ensure all persons are clear of moving components before performing a movement. Maintenance to be carried out by a competent person.	
4.11	Faulty/out of order, or poorly maintained plant	Crushing Impact Trauma	Operation Emergency Maintenance	Operator's manual outlines plant maintenance schedule. Current maintenance inspections up to date as per manufacturers	B4 High	Always perform pre-operation inspection before operating the plant. Implement 'tag out' procedure to isolate faulty/out of order plants.	B1 Low
				recommendation.		Do not use an 'out of order' plant. Record all faults in logbook.	
						Perform plant maintenance as per manufacturer's maintenance schedule.	
						Keep maintenance records / plant logbook up to date.	
4.12	Refuelling	Explosion Fire			B4 High	 When refuelling: Keep away from ignition sources; Do not smoke; Avoid spilling fuel over hot engine. 	B1 Low
4.13	Poor ventilation	Asphyxiation	Operation	Plant run off electric motor.		Ensure that the unit is operated only in well-ventilated areas.	
4.14	Engine exhaust pipe	Burn	Operation	Exhaust pipe guarded. "Hot surface" decal in place.	C2 Medium	Do not touch exhaust pipe when hot.	A1 Low
4.15	Plant modifications after completion of risk assessment.	Crushing Overturning	Operation Set up		C5 Extreme	Ensure modifications made to the plant are inspected, assessed, and approved by a competent person. Review hazard analysis and risk assessment after plant modifications.	B1 Low

Title: Authorised By: Plant Risk Assessment

Managing Director

Document Number: 01

Revision: 01 **Date:** 11 Sep. 2024 Page:

ID	Description of	Hazard Potential	Activity	Risk control measures already	Risk	Supplementary risk control	Risk
	Origin	Consequence		implemented		measures	score
5	Transport						
5.1	Loading and unloading – driving on	Roll over Crushing	Transport	Use remote controls always as they provide a safe operating distance for loading / unloading. Use low speed / low engine RPM on slopes / ramps.	C4 Extreme	Follow appropriate loading procedures including using weight rated ramps, have ramps at a low inclination, all person clear from the loading zone and placing the heavy end towards the front of the tray or tow hitch on a trailer.	B2 Low
5.2	Loading and unloading – lifting on	Crush Impact	Transport Lifting	Lifting procedure included in Operator's Manual.	C5 Extreme	Follow appropriate lifting procedure.	B2 Low
5.3	Failure of lifting slings / chains used for lifting or tying down / tie down straps	Roll over Crushing	Transport Lifting	Plant is fitted with designated lifting and tied down points.	C5 Extreme	Use tie-down points provided on the plant to secure it for transportation. Ensure lifting slings and tie down straps are in good condition. Ensure lifting slings have a SWL suited to the load.	B2 Low
6	Plant Failure						
6.1	Plant failure including: - malfunction of control devices - structural failure of machine components	Crushing Impact	Storage Operation Setup	Follow routine maintenance inspections by qualified person as per manufacturers recommendation. Prestart inspection as per manufacturers recommendation.	B5 Extreme	Carry out pre-operational function tests of safety related functions at the start of every shift. Beware of risks associated with inadvertent operation of the machine, avoid compromising machine positions. Familiarise with location of emergency stop buttons. Regularly inspect the plant as per maintenance schedule to ensure integrity of structural members.	B2 Low

Document Number: 01

Date: 11 Sep. 2024

Revision: 01

THIS DOCUMENT IS CONTROLLED – UNCONTROLLED WHEN PRINTED

ID	Description of	Hazard Potential	Activity	Risk control measures already	Risk	Supplementary risk control	Risk
	Origin	Consequence		implemented		measures	score
6.2	Remote control failure	Crushing Impact Uncontrolled movement		Remote control system intrinsically safe, all functions stop if a failure occurs.	A4 High	Ensure remote control battery is fully charged before the start of a job. Test operation of emergency stop buttons at the start of every job.	A1 Low
6.3	Failure of cylinder or hose resulting in uncontrolled movement.	Crushing Overturning Burn Skin irritation	Set up Operation Maintenance	Cylinders are fitted with load holding check valves to prevent movement in case of hose failure. Hydraulic filters fitted	A3 Medium	Check hydraulic hose condition during periodic maintenance. Report and "tag out of service" if identified.	A2 Low
6.4	Excessive hydraulic oil pressure.	Impact Crushing	Set up Operation	Plant fitted with pressure relief valve.	C3 High	Check pressure settings during preventative maintenance.	A1 Low
6.5	High pressure fluid injection	Injection injury	Operation	Hose sleeving is fitted to all hydraulic hoses in proximity to the operator. A pressure relief valve is installed which limits the maximum system pressure.		Ensure that the correct pressure setting is maintained as per the operation manual instructions. Visually inspect the plant for hydraulic leaks.	
6.6	Emergency Stop not available	Crushing Impact Trauma	Emergency Maintenance		C4 Extreme	Check that the emergency stop button functions correctly.	A1 Low
6.7	Inadequate maintenance procedures	Crushing Impact	Maintenance	Maintenance procedures included in Operator's Manual.	B4 High	Allow only qualified service personnel to perform maintenance tasks.	B1 Low
7	Electrical						
7.1	Damaged power cables, components.	Electrocution Shock Fire	Set up Operation Maintenance Troubleshoot	RCD fitted to 240V circuit. Fuse protection on electrical circuits	C1 Low	Ensure plant and extension cord are electrically tested and tagged as per AS 3760. Do not operate/use equipment	B1 Low
			Emergency			with an expired test tag. Ensure inline RCD is used when charging the batteries.	

Title:
Authorised By:
© Monitor 2023

Plant Risk Assessment Managing Director Document Number: 01

Page:

ID	Description of	Hazard Potential	Activity	Risk control measures already	Risk	Supplementary risk control	Risk
	Origin	Consequence		implemented		measures	score
						Visually inspect the plant and extension lead before resetting the thermal fuse and RCD.	
7.2	Electric shock from fault in power supply	Electrocution Shock Fire	Set up Operation Maintenance	Main power disconnect switch fitted.	C4 Extreme	Ensure AC power supply has an earth leakage circuit breaker fitted. Use appropriate means to supply power to the plant. That is, use extension leads with neutral, live and earth wire and pin. Ensure the plant's appliance inlet is regularly tested and tagged as per AS 3760. Do not operate a plant with an expired electrical safety tag. Visually inspect the plant and extension lead before turning the power ON.	A2 Low
7.3	Power extension lead overheating.	Electrocution Shock Fire	Set up Operation Maintenance Troubleshoot Emergency		C4 Extreme	Use appropriate means to supply power to the plant. That is, only use extension leads rated to plant requirements. Ensure the plant's appliance inlet is regularly tested and tagged as per AS 3760. Do not operate a plant with an expired electrical safety tag.	A3 Medium
7.4	Power failure (flat battery)	Crushing Being runover	Operation Emergency		C4 Extreme	Prepare emergency procedure for power failure.	C1 Low

© Monitor 2023

Managing Director

THIS DOCUMENT IS CONTROLLED – UNCONTROLLED WHEN PRINTED

Document Number: 01

Revision: 01

Date: 11 Sep. 2024

ID	Description of Hazard Potential		Activity Risk control measures already		Risk	Supplementary risk control	Risk
	Origin	Consequence	_	implemented		measures	score
7.5	Battery charging	Burn Fire Explosion	Maintenance		C5 Extreme	Charge in an area with good ventilation, away from ignition sources. Ensure that the battery is disconnected before charging.	A3 Medium
7.6	Battery handling	Burn Fire Explosion	Maintenance	Battery disconnect switch provided.	C5 Extreme	When handling the battery, wear protective clothing and eyewear. Avoid contact with clothes or skin; if electrolyte gets on your skin or clothes, flush it with a large quantity of water. In case of contact with eyes, flush with a lot of water for at least 15 minutes and seek medical assistance immediately. Do not touch the battery terminals or cables with tools that may cause spark emissions. In order to avoid spark emissions, always disconnect the (-) cable first and connect it last. Use appropriate lifting techniques, perform 2 person lifting technique for heavy or awkward to reach parts.	3B Low
7.7	Contact with overhead power lines.	Electrocution	Set up Operation Transport Emergency	Warning decal on machine.	C5 Extreme	Maintain safe distance from powerlines. Ensure overhead power is switched off or use a spotter if safe distances cannot be maintained.	A3 Medium

© Monitor 2023

Managing Director

THIS DOCUMENT IS CONTROLLED – UNCONTROLLED WHEN PRINTED

Document Number: 01

Revision: 01

Date: 11 Sep. 2024

Page:

ID	Description of	Hazard Potential	Activity	Risk control measures already	Risk	Supplementary risk control	Risk
	Origin	Consequence		implemented		measures	score
						Be mindful of overhead power lines on roads when transporting the plant on a vehicle.	
						Do not move, approach or come in contact with a plant that has contacted power lines until network power has been isolated.	
7.8	Lightning	Electrocution Shock	Set up Operation		A5 High	Do not use the plant during a thunderstorm.	A1 Low
8	Crane Components						
8.1	Suspended load / hook block swinging due to wind or	Crushing Impact	Operation	Crush hazard decals on plant	C4 Extreme	Use tag line to control suspended load movement.	B1 Low
	movement of the					Keep plant operating area clear of obstructions.	
	plant.					Install safety barriers around the working area to prevent unauthorised access.	
8.2	Incorrect set up of	Structural failure.	Operation		B5	Regularly test operation of block.	A2
	lifting block.				Extreme	Install an anti-two block limiting device.	Low
8.3	Lifting block: raising before it hits head of the boom.	Cushing Impact Structural failure Damage to rope and pulleys Overturning	Operation	Operator's manual states the block must not be raised until it hits the head of the boom	D3 High	If crane is equipped with a device to disengage the lifting block before it hits the head of the boom, it must be checked for correct operation before each use of the crane.	A2 Low
						Regularly inspect wire rope for signs of wear/damage.	
8.4	Wire rope failure	Crushing	Set up		C5	Always perform pre-operation	B2
			Operation Maintenance		Extreme	inspection before operating the plant.	Low

© Monitor 2023

Document Number: 01

Date: 11 Sep. 2024

Revision: 01

THIS DOCUMENT IS CONTROLLED – UNCONTROLLED WHEN PRINTED

ID	Description of	Hazard Potential	Activity	Risk control measures already	Risk	Supplementary risk control	Risk
	Origin	Consequence	_	implemented		measures	score
						Keep maintenance records / plant log book up to date.	
						Replace wire rope at service intervals recommended by the manufacturer.	
8.5	Rigging equipment failure. - Using chains and slings not rated for lifting.	Crushing Impact	Operation Maintenance		C5 Extreme	Plan lift beforehand, ensure rigging equipment is in good condition and have rated capacities suitable for the load being lifted.	A2 Low
	- Incorrect load rating of shackles, hooks					Ensure rigging equipment is inspected, regularly maintained and tagged with inspection dates.	
	and lifting slings.					Do not use rigging equipment with out of-date tags.	
						Do not use ropes for lifting operations.	
8.6	Plant component movement	Crushing Impact Shearing Drawing Severing	Set up Operation Maintenance	Plant fitted with guards to cover engine and slewing mechanism. Crush and impact hazard decals fitted to the plant.	C3 High	Install safety barriers around the working area to prevent unauthorised access. Maintain a safe distance from moving parts of the plant.	A2 Low
8.7	Winch, wire rope, sheaves, hook block, winch head	Drawing-in Severing Crushing	Set up Operation Maintenance	integrate the plants	C4 Extreme	Add pinch point safety decal throughout wire rope path, including winch.	A2 low
						Do not wear loose cloth, ties while operating or standing near the plant.	
8.8	Incorrect/incomplete assembly of hook block.	Crushing	Set up Operation	Hook assembly procedure shown in operator's manual.	B4 High	Wear appropriate PPE. Follow operating procedure to assemble the hook block.	B1 Low

© Monitor 2023

Managing Director

THIS DOCUMENT IS CONTROLLED – UNCONTROLLED WHEN PRINTED

Document Number: 01

Revision: 01

Date: 11 Sep. 2024 Page:

ID	Description of Hazard Potential		Activity	Risk control measures already	Risk	Supplementary risk control	Risk
	Origin	Consequence		implemented		measures	score
8.9	Incorrect feeding of wire rope.	Crushing	Set up Operation		B4 High	Ensure wire rope is fed following markers on the plant.	B1 Low
						Add wire rope routing diagram to the plant for all different attachment configurations.	
8.10	Buckling of extension system/jib due to dead-ending of winch rope.	Crushing Impact Overturning	Operation		B5 Extreme	Ensure that the hook doesn't contact the end of the extension / jib during hoisting or extending motions. Install an anti-two block limiting device.	B1 Low
8.11	Wire rope incorrect winding (birds nest)	Crushing Impact	Operation		B5 Extreme	Avoid hoisting with slack on the wire rope.	A2 Low
						Ensure hook weight is installed. Do not stand or place limbs under a raised load.	
8.12	Effect of boom deflection under load.	Electrocution Shock Fire Impact	Operation Maintenance	Caution given in operator's manual about large boom deflections under load.	C4 Extreme	Observe boom movement when releasing the load to ensure there is a safe distance from electric power lines.	A3 Medium
						Follow local authority safe distance guidelines when working near overhead power lines.	
						Slowly lower load to avoid boom whiplash.	
						Avoid sudden changes in boom/turntable direction.	
						Maintain a safe distance from the boom and load until the load is completely released.	
8.13	Pushing/pulling ballast	Musculoskeletal disorder	Set up Maintenance		C3 High	Regularly service ballast slide to ensure smooth operation.	A3 Medium

Title: Plant Risk Assessment

Managing Director

Authorised By:

© Monitor 2023

Revision: 01 Document Number: 01

Date: 11 Sep. 2024

Page:

ID	Description of Hazard Potential		Activity	Risk control measures already	Risk	Supplementary risk control	Risk
	Origin	rigin Consequence		implemented		measures	score
						Use sound ergonomic techniques to avoid back injuries.	
8.14	Operating machine with ballast.	Crushing Impact	Set up Maintenance		B3 Medium	Remove or reduce ballast when operating machine to prevent reduction in machine movement and overload of components. Do not apply ballast while travelling to prevent overloading the tracks.	A2 Low
8.15	Installing/uninstalling fly jib and other attachments.	Crushing Impact Shearing	Assembly Set up	General warnings in operator's manual recommend the use of gloves when feeding the winch cable	D2 High	Wear appropriate protective gear such as gloves and eye protection. Avoid lifting heavy plant components. Seek help if items are too heavy.	A2 Low

Title:Plant Risk AssessmentDocument Number: 01Authorised By:Managing Director

© Monitor 2023

Date: 11 Sep. 2024

THIS DOCUMENT IS CONTROLLED – UNCONTROLLED WHEN PRINTED

Revision: 01

RISK MATRIX						ACTION	HEIRACHY OF CONTROLS	
		CONSEQUENCE				EXTREME – Do not proceed,	Elimination – controlling the hazard at	
		1. Insignificant	2. Minor	3. Moderate	4. Major	5. Catastrophic	until further control measures are implemented to lower the risk. Senior management attention required. HIGH – Review and introduce	the source 2. Substitution – e.g. replacing one substance or activity with a less
ПКЕПНООБ	E. Almost Certain Is expected to occur immediately or within a short timeframe	HIGH	HIGH	EXTREME	EXTREME	EXTREME		hazardous one 3. Isolation – e.g. use of barriers to shield of isolate the hazard, enclosures for noisy
	D. Likely Will probably occur in most circumstances	MEDIUM	HIGH	HIGH	EXTREME	EXTREME	additional controls to lower level of risk. Needs senior management attention.	machinery, installing guards on machinery 4. Engineering – e.g. design and install
	C. Possible Could happen and has occurred here or elsewhere	LOW	MEDIUM	HIGH	EXTREME	EXTREME	MEDIUM – Monitor and maintain supervision and	equipment to counteract the hazard 5. Administration – policies and procedures for safe work practices
	B. Unlikely Unlikely to occur	LOW	LOW	MEDIUM	HIGH	EXTREME	controls. Specify management responsibility.	 Personal Protective Equipment – e.g. respirators, ear plugs, face masks, safety glasses, safety shoes
	A. Rare Not expected to occur	LOW	LOW	MEDIUM	HIGH	HIGH	LOW – Monitor and manage by routine procedures and monitoring.	glasses, sureey strong

CONSEQUENCE DESCRIPTORS							
SEVERITY	SAFETY	ENVIRONMENT	BUSINESS				
5. Catastrophic	Potential for incident resulting in serious damage and/or fatality	The aspect is legally or contract regulated and has the potential for a disastrous long term impact resulting in prosecution.	Loss > \$1M				
4. Major	Potential for incident resulting in serious damage and/or permanent disabling illness or injury	The aspect is legally or contract regulated and has the potential for a serious long term impact resulting in prosecution.	Loss of service provision				
3. Moderate	Potential for incident resulting in significant damage and/or temporary disabling illness or injury	Significant environmental aspect with short term impact resulting in improvement notice.	Loss \$100K - \$1M				
2. Minor	Potential for incident resulting in moderate damage and/or requiring medical treatment.	The aspect is legally or contract regulated and has the potential for a moderate reversible short term impact resulting in an improvement notice.	Prolonged reduction in service provision or productivity				
1. Insignificant	Potential for incident resulting in minor damage and/or injury requiring first aid treatment	The aspect is not legally or contract regulated and has the potential for a minor negligible impact.	Loss \$10K - \$100K				

Title:Plant Risk AssessmentDocument Number: 01Revision:01Authorised By:Managing DirectorDate:11 Sep. 2024